



# IO-Link Data Reference Guide

This document refers to the following IODD file: Banner\_Engineering-IC70-16P-K-20241101-IODD1.1.xml. The IODD file and support files can be found on [www.bannerengineering.com](http://www.bannerengineering.com) under the download section of the product family page.

## Communication Parameters

Parameter	Value	Parameter	Value
IO-Link revision	V1.1	Port class	A
Process data in length	16-bits	SIO mode	Yes
Process data out length	16-bits	Smart sensor profile	No
Bit rate	38400 bps	Block parameterization	Yes
Minimum cycle time	3.3 ms	Data storage	Yes
Device ID	659478		

## Process Data In (Device to Master)

Subindex	Name	Number of Bits	Data Values
1	Channel 1 Input State	1	false=inactive, true=active
2	Channel 2 Input State	1	false=inactive, true=active
3	Channel 3 Input State	1	false=inactive, true=active
4	Channel 4 Input State	1	false=inactive, true=active
5	Channel 5 Input State	1	false=inactive, true=active
6	Channel 6 Input State	1	false=inactive, true=active
7	Channel 7 Input State	1	false=inactive, true=active
8	Channel 8 Input State	1	false=inactive, true=active
9	Channel 9 Input State	1	false=inactive, true=active
10	Channel 10 Input State	1	false=inactive, true=active
11	Channel 11 Input State	1	false=inactive, true=active
12	Channel 12 Input State	1	false=inactive, true=active
13	Channel 13 Input State	1	false=inactive, true=active
14	Channel 14 Input State	1	false=inactive, true=active
15	Channel 15 Input State	1	false=inactive, true=active
16	Channel 16 Input State	1	false=inactive, true=active

*Octet 0*

Subindex	8	7	6	5	4	3	2	1
Bit offset	15	14	13	12	11	10	9	8
Value	1	1	1	1	1	1	0	1

*Octet 1*

Subindex	16	15	14	13	12	11	10	9
Bit offset	7	6	5	4	3	2	1	0
Value	1	1	1	0	1	1	1	0

*Example based on the listed values*

1	Channel 1 input state	active	9	Channel 9 input state	inactive
2	Channel 2 input state	inactive	10	Channel 10 input state	active

Continued on page 2



Continued from page 1

3	Channel 3 input state	active	11	Channel 11 input state	active
4	Channel 4 input state	active	12	Channel 12 input state	active
5	Channel 5 input state	active	13	Channel 13 input state	inactive
6	Channel 6 input state	active	14	Channel 14 input state	active
7	Channel 7 input state	active	15	Channel 15 input state	active
8	Channel 8 input state	active	16	Channel 16 input state	active

## Process Data Out (Master to Device)

Subindex	Name	Number of Bits	Data Values
1	Channel 1 Output State	1	false=Off/InActive, true=On/Active
2	Channel 2 Output State	1	false=Off/InActive, true=On/Active
3	Channel 3 Output State	1	false=Off/InActive, true=On/Active
4	Channel 4 Output State	1	false=Off/InActive, true=On/Active
5	Channel 5 Output State	1	false=Off/InActive, true=On/Active
6	Channel 6 Output State	1	false=Off/InActive, true=On/Active
7	Channel 7 Output State	1	false=Off/InActive, true=On/Active
8	Channel 8 Output State	1	false=Off/InActive, true=On/Active
1	Channel 9 Output State	1	false=Off/InActive, true=On/Active
2	Channel 10 Output State	1	false=Off/InActive, true=On/Active
3	Channel 11 Output State	1	false=Off/InActive, true=On/Active
4	Channel 12 Output State	1	false=Off/InActive, true=On/Active
5	Channel 13 Output State	1	false=Off/InActive, true=On/Active
6	Channel 14 Output State	1	false=Off/InActive, true=On/Active
7	Channel 15 Output State	1	false=Off/InActive, true=On/Active
8	Channel 16 Output State	1	false=Off/InActive, true=On/Active

### Octet 0

Subindex	8	7	6	5	4	3	2	1
Bit offset	15	14	13	12	11	10	9	8

### Octet 1

Subindex	16	15	14	13	12	11	10	9
Bit offset	7	6	5	4	3	2	1	0

## Parameters Set Using IO-Link

These parameters can be read from and/or written to an IC70-16P-K IO-Link Hub. Also included is information about whether the variable in question is saved during data storage and whether the variable came from the IO-Link Smart Sensor Profile. Unlike process data in, which is transmitted from the IO-Link device to the IO-Link master cyclically, these parameters are read or written acyclically as needed.

Index	Subindex	Name	Length	Value Range	Default	Access Rights	Data Storage?
0	1-16	Direct Parameter Page 1 (incl. Vendor ID & Device ID)				ro	
1	1-16	Direct Parameters Page 2				rw	
2		System Command		130 = Restore Factory Settings 162 = Start discovery 163 = Stop discovery 164 = Reset All Metrics		wo	
3		Data Storage Index (device-specific list of parameters to be stored)				rw	
4-11		reserved by IO-Link Specification					

Continued on page 3

Continued from page 2

Index	Subindex	Name	Length	Value Range	Default	Access Rights	Data Storage?
<b>12</b>		<b>Device Access Locks</b>					
12	1	Parameter Write Access Lock		0 = off, 1 = on	0	rw	y
12	2	Data Storage Lock		0 = off, 1 = on	0	rw	y
12	3	Local Parameterization Lock		0 = off, 1 = on	0	rw	y
12	4	Local User Interface Lock		0 = off, 1 = on	0	rw	y
16		Vendor Name string		Banner Engineering Corporation		ro	
17		Vendor Text string		More Sensors. More Solutions.		ro	
18		Product Name string		IC70-16P-K		ro	
19		Product ID string		IC70-16P-K		ro	
20		Product Text string				ro	
21		Serial Number				ro	
23		Firmware Version				ro	
24		App Specific Tag (user-defined)				rw	y
36		Device Status	8-bit integer	0=Device is OK, 1=Maintenance required, 2=Out of specification, 3=Functional check, 4=Failure, 5..255 Reserved		ro	
37		Detailed Device Status	Array[6] of 3-octet			ro	
38-39		reserved					
40		Process Data Input		see Process Data In		ro	
41		Process Data Output		see Process Data Out		ro	
42-57		unused/reserved					
<b>69</b>		<b>All-Time Run Time</b>					
69	1	Run counter	32-bit Uinteger	0..2147483647		ro	y
<b>70</b>		<b>Resettable Run Time</b>					
70	1	Run counter	32-bit Uinteger	0..2147483647	0	rw	
<b>78</b>		<b>All-Time Run Time Event Time</b>					
78	1	Event Time	32-bit Uinteger	0..2147483647	0	rw	y
<b>79</b>		<b>Resettable Run Time Event Time</b>					
79	1	Event Time	32-bit Uinteger	0..2147483647	0	rw	y
<b>80</b>		<b>IO Metrics Channels 1 to 8</b>					
80	1	Channel 1 Count	32-bit Uinteger	0..2147483647		ro	
80	2	Channel 1 Count Duration -	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
80	3	Channel 1 Count Events per Minute	32-bit Uinteger	1..300000		ro	
80	4	Channel 1 CountTotalizer Counter	32-bit Uinteger	0..2147483647		ro	
80	5	Channel 2 Count	32-bit Uinteger	0..2147483647		ro	
80	6	Channel 2 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
80	7	Channel 2 Events per Minute	32-bit Uinteger	1..300000		ro	
80	8	Channel 2 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
80	9	Channel 3 Count	32-bit Uinteger	0..2147483647		ro	
80	10	Channel 3 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
80	11	Channel 3 Events per Minute	32-bit Uinteger	1..300000		ro	
80	12	Channel 3 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
80	13	Channel 4 Count	32-bit Uinteger	0..2147483647		ro	
80	14	Channel 4 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
80	15	Channel 4 Events per Minute	32-bit Uinteger	1..300000		ro	
80	16	Channel 4 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
80	17	Channel 5 Count	32-bit Uinteger	0..2147483647		ro	
80	18	Channel 5 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	

Continued on page 4

Continued from page 3

Index	Subindex	Name	Length	Value Range	Default	Access Rights	Data Storage?
80	19	Channel 5 Events per Minute	32-bit Uinteger	1..300000		ro	
80	20	Channel 5 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
80	21	Channel 6 Count	32-bit Uinteger	0..2147483647		ro	
80	22	Channel 6 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
80	23	Channel 6 Events per Minute	32-bit Uinteger	1..300000		ro	
80	24	Channel 6 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
80	25	Channel 7 Count	32-bit Uinteger	0..2147483647		ro	
80	26	Channel 7 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
80	27	Channel 7 Events per Minute	32-bit Uinteger	1..300000		ro	
80	28	Channel 7 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
80	29	Channel 8 Count	32-bit Uinteger	0..2147483647		ro	
80	30	Channel 8 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
80	31	Channel 8 Events per Minute	32-bit Uinteger	1..300000		ro	
80	32	Channel 8 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
<b>81</b>		<b>IO Metrics Channels 9 to 16</b>					
81	1	Channel 9 Count	32-bit Uinteger	0..2147483647		ro	
81	2	Channel 9 Duration -	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
81	3	Channel 9 Events per Minute	32-bit Uinteger	1..300000		ro	
81	4	Channel 9 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
81	5	Channel 10 Count	32-bit Uinteger	0..2147483647		ro	
81	6	Channel 10 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
81	7	Channel 10 Events per Minute	32-bit Uinteger	1..300000		ro	
81	8	Channel 10 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
81	9	Channel 11 Count	32-bit Uinteger	0..2147483647		ro	
81	10	Channel 11 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
81	11	Channel 11 Events per Minute	32-bit Uinteger	1..300000		ro	
81	12	Channel 11 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
81	13	Channel 12 Count	32-bit Uinteger	0..2147483647		ro	
81	14	Channel 12 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
81	15	Channel 12 Events per Minute	32-bit Uinteger	1..300000		ro	
81	16	Channel 12 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
81	17	Channel 13 Count	32-bit Uinteger	0..2147483647		ro	
81	18	Channel 13 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
81	19	Channel 13 Events per Minute	32-bit Uinteger	1..300000		ro	
81	20	Channel 13 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
81	21	Channel 14 Count	32-bit Uinteger	0..2147483647		ro	
81	22	Channel 14 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
81	23	Channel 14 Events per Minute	32-bit Uinteger	1..300000		ro	
81	24	Channel 14 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
81	25	Channel 15 Count	32-bit Uinteger	0..2147483647		ro	
81	26	Channel 15 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
81	27	Channel 15 Events per Minute	32-bit Uinteger	1..300000		ro	
81	28	Channel 15 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
81	29	Channel 16 Count	32-bit Uinteger	0..2147483647		ro	
81	30	Channel 16 Duration	32-bit Uinteger	0..2147483647, 50µS resolution		ro	
81	31	Channel 16 Events per Minute	32-bit Uinteger	1..300000		ro	
81	32	Channel 16 Totalizer Counter	32-bit Uinteger	0..2147483647		ro	
<b>82</b>		<b>Selectable Metric Reset</b>					
82	1	Channel 1	Boolean	false=Do Not Reset, true=Reset	false	rw	

Continued on page 5

Continued from page 4

Index	Subindex	Name	Length	Value Range	Default	Access Rights	Data Storage?
82	2	Channel 2	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	3	Channel 3	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	4	Channel 4	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	5	Channel 5	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	6	Channel 6	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	7	Channel 7	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	8	Channel 8	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	9	Channel 9	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	10	Channel 10	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	11	Channel 11	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	12	Channel 12	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	13	Channel 13	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	14	Channel 14	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	15	Channel 15	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	16	Channel 16	Boolean	false=Do Not Reset, true=Reset	false	rw	
82	17	Channel 1 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	18	Channel 1 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	19	Channel 3 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	20	Channel 4 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	21	Channel 5 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	22	Channel 6 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	23	Channel 7 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	24	Channel 8 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	25	Channel 9 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	26	Channel 10 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	27	Channel 11 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	28	Channel 12 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	29	Channel 13 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	30	Channel 14 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	31	Channel 15 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
82	32	Channel 16 Reset Count	32-bit Uinteger	0..2147483647	0	rw	
<b>87</b>		<b>Channel 1 Configuration</b>					
87	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
87	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
87	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
87	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
87	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
87	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
87	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>88</b>		<b>Channel 2 Configuration</b>					
88	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
88	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y

Continued on page 6

Continued from page 5

Index	Subindex	Name	Length	Value Range	Default	Access Rights	Data Storage?
88	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
88	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
88	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
88	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
88	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>89</b>		<b>Channel 3 Configuration</b>					
89	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
89	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
89	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
89	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
89	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
89	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
89	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>90</b>		<b>Channel 4 Configuration</b>					
90	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
90	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
90	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
90	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
90	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
90	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
90	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>91</b>		<b>Channel 5 Configuration</b>					
91	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
91	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
91	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
91	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
91	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
91	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
91	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>92</b>		<b>Channel 6 Configuration</b>					
92	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y

Continued on page 7

Continued from page 6

Index	Subindex	Name	Length	Value Range	Default	Access Rights	Data Storage?
92	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
92	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
92	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
92	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
92	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
92	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>93</b>		<b>Channel 7 Configuration</b>					
93	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
93	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
93	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
93	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
93	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
93	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
93	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>94</b>		<b>Channel 8 Configuration</b>					
94	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
94	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
94	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
94	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
94	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
94	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
94	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>95</b>		<b>Channel 9 Configuration</b>					
95	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
95	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
95	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
95	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
95	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
95	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y

Continued on page 8

Continued from page 7

Index	Subindex	Name	Length	Value Range	Default	Access Rights	Data Storage?
95	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>96</b>		<b>Channel 10 Configuration</b>					
96	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
96	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
96	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
96	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
96	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
96	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
96	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>97</b>		<b>Channel 11 Configuration</b>					
97	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
97	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
97	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
97	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
97	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
97	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
97	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>98</b>		<b>Channel 12 Configuration</b>					
98	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
98	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
98	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
98	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
98	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
98	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
98	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>99</b>		<b>Channel 13 Configuration</b>					
99	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
99	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
99	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
99	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
99	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y

Continued on page 9



Continued from page 8

Index	Subindex	Name	Length	Value Range	Default	Access Rights	Data Storage?
99	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
99	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>100</b>		<b>Channel 14 Configuration</b>					
100	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
100	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
100	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
100	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
100	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
100	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
100	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>101</b>		<b>Channel 15 Configuration</b>					
101	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
101	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
101	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
101	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
101	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
101	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
101	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y
<b>102</b>		<b>Channel 16 Configuration</b>					
102	1	IO Selection	8-bit Uinteger	1=PNP Input, 3=PNP Output with Pull Down	3	rw	y
102	2	Delay Mode	8-bit Uinteger	0 = Disabled, 1 = On Off Delay, 2 = On One-shot, 3 = Off One-shot, 4 = On Pulse-stretcher, 5 = Off Pulse-stretcher, 6 = Totalizer, 7 = Retriggerable On One-shot, 8 = Retriggerable Off One-Shot	0	rw	y
102	3	Delay Timer 1	32-bit Uinteger	0..2147483647 [Channel On Delay, One-shot, Pulse-stretcher time(ms) or Totalizer Count]	0	rw	y
102	4	Delay Timer 2	32-bit Uinteger	0..2147483647 (Channel Off Delay or Totalizer time)ms	0	rw	y
102	5	Mirroring Enable	8-bit Uinteger	0=Disabled, 1=Enabled	0	rw	y
102	6	Mirroring Channel Selection	8-bit Uinteger	0=Channel 1, 1=Channel 2, 2=Channel 3, 3=Channel 4, 4=Channel 5, 5=Channel 6, 6=Channel 7, 7=Channel 8, 8=Channel 9, 9=Channel 10, 10=Channel 11, 11=Channel 12, 12=Channel 13, 13=Channel 14, 14=Channel 15, 15=Channel 16	0	rw	y
102	7	Mirroring Inversion	8-bit Uinteger	0=Not Inverted, 1=Inverted	0	rw	y

## IO-Link Events

---

Events are acyclic transmissions from the IO-Link device to the IO-Link master. Events can be error messages and/or warning or maintenance data.

Code	Type	Name	Description
25376 (0x6320)	Error	Parameter error	Check datasheet and values
36000 (0x8CA0)	Warning	All-time Run Time Event	Event indicating the corresponding configured running time has elapsed.
36001 (0x8CA1)	Warning	Resettable Run Time Event	Event indicating the corresponding configured running time has elapsed.