

S15C Analog Converter (Voltage and Current) - IO-Link Data Reference Guide



IO-Link Data Map

This document refers to the following IODD file: Banner_Engineering-S15C-IU-20200715-IODD1.1.xml. The IODD file and support files can be found on www.bannerengineering.com under the download section of the product family page.

Communication Parameters

The following communication parameters are used.

Parameter	Value	Parameter	Value
IO-Link revision	V1.1	Port class	A
Process Data In length	32 bits	SIO mode	Yes
Process Data Out length	N/A	Smart Sensor Profile	Yes
Bit Rate	38400 bps	Block parameterization	Yes
Minimum cycle time	3.6 ms	Data Storage	Yes

IO-Link Process Data In (Device to Master)

Process Data In is transmitted cyclically to the IO-Link master from the IO-Link device.

Two analog files are supported by the IODD file. The voltage model is presented in mV and the current mode is presented in μ A.

If the model is the voltage version, then Process Data Input = value $\times$ 0.001 V.

If the model is the current version, then Process Data Input = value $\times$ 0.000001 A.

Process Data Input output - Analog Data

Subindex	Name	Number of Bits	Data Values
1	Measurement Value	32	The measurement device value

Example Process Data Input output - Analog Data (Voltage Model)

Octet 0								
Subindex	1	1	1	1	1	1	1	1
Bit offset	31	30	29	28	27	26	25	24
Value	0	0	0	0	0	0	0	0
Octet 1								
Subindex	1	1	1	1	1	1	1	1
Bit offset	23	22	21	20	19	18	17	16
Value	0	0	0	0	0	0	0	0
Octet 2								
Subindex	1	1	1	1	1	1	1	1
Bit offset	15	14	13	12	11	10	9	8
Value	0	0	0	0	0	0	0	1
Octet 3								
Subindex	1	1	1	1	1	1	1	1
Bit offset	7	6	5	4	3	2	1	0
Value	1	1	1	1	1	1	0	1



Example Based Upon the Value Above

Measurement Value = 509

Scaled Measurement Value = 0.509 V

Process Data Input on ION - Digital Measuring Sensor

Subindex	Name	Number of Bits	Data Values
1	Measurement Value	16	The measurement device value
2	Measurement Scale	8	The measurement device scale Voltage = -3 Current = -6

Example Process Data Input on ION - Digital Measuring Sensor (Voltage Model)

Octet 0								
Subindex	1	1	1	1	1	1	1	1
Bit offset	31	30	29	28	27	26	25	24
Value	0	0	0	0	0	0	0	1
Octet 1								
Subindex	1	1	1	1	1	1	1	1
Bit offset	23	22	21	20	19	18	17	16
Value	1	1	1	1	1	1	0	1
Octet 2								
Subindex	2	2	2	2	2	2	2	2
Bit offset	15	14	13	12	11	10	9	8
Value	0	0	0	0	0	0	1	1
Octet 3								
Subindex	///	///	///	///	///	///	///	///
Bit offset	7	6	5	4	3	2	1	0
Value								

Example Based Upon the Value Above

Measurement Value = 509

Measurement Scale = -3

Scaled Measurement Value = 0.509 V

Parameters Set Using IO-Link

These parameters can be read from and/or written to an S15C-I-KQ or S15C-U-KQ converter. Also included is information about whether the variable in question is saved during Data Storage and whether the variable came from the IO-Link Smart Sensor Profile. Unlike Process Data In, which is transmitted from the IO-Link device to the IO-Link master cyclically, these parameters are read or written acyclically as needed.

Index	Sub-index	Name	Length	Value Range	Default	Access Rights	Data Storage?	Smart Sensor Profile
0	1-16	Open Parameters Page 1 (incl. Vendor ID & Device ID)			0			
1	1-16	Open Parameters Page 2				r/w		
2		Standard Command		130 = Restore Factory Settings 162 = Self discovery 163 = Self discovery		w0		y
3		Data Storage Index (device specific list of parameters to be stored)				r/w		

Index	Sub-index	Name	Length	Value Range	Default	Access Rights	Data Storage?	Smart Sensor Profile
4 11		reserved by IO-Link Specification						
12		Device Access Locks						
12	1	Parameter Write Access Lock		0 = off, 1 = on	0	r/w	y	
12	2	Data Storage Lock		0 = off, 1 = on	0	r/w	y	
12	3	Local Parameterization Lock		0 = off, 1 = on	0	r/w	y	
12	4	Local User Interface Lock		0 = off, 1 = on	0	r/w	y	
13		Profile Characteristic				r		
14		POutput Descriptor				r		
15		POutput Descriptor				r		
16		Vendor Name string		Banner Engineering Corporation		r		
17		Vendor Text string		More Sensors. More Solutions.		r		
18		Product Name string				r		
19		Product ID string				r		
20		Product Text string				r		y
21		Serial Number				r		
22		Hardware Version				r		
23		Firmware Version				r		y
24		App Specific Tag (user defined)				r/w	y	y
25		Function Tag				r/w	y	y
26		Location Tag				r/w	y	y
27 36		reserved						
36		Device Status	8 bit Integer	0 = Device is OK 1 = Maintenance required 2 = Out of specification 3 = Functional check 4 = Failure 5..255 Reserved		r		
37		Delayed Device Status	Array[8] of 3 bits			r		
38 39		reserved						
40		Process Output Input		see Process Data In		r		
41 57		unused/reserved						
60		BDC1 Setpoints						
60	1	Segment SP1	32 bit Integer		0.004 A 0.2 V	r/w		
60	2	Segment SP2	32 bit Integer		0.02 A 10 V	r/w		
61		BDC1 Configuration						
61	1	reserved	8 bit Unsigned					
61	2	reserved						
61	3	Hysteresis	16 bit Unsigned		0.0001 A 0.05 V	r/w		
69		All-Time Run Time						
69	1	Run counter	32 bit Unsigned	0..2147483647		r	y	
70		Resettable Run Time						
70	1	Run counter	32 bit Unsigned	0..2147483647	0	r/w		
76		Vendor Specific Configuration						
76	1	Process Output Input Configuration	8 bit Unsigned	0 = Analog Value 1 = Digital Measurement Value	0	r/w		
76	2	IO-Link Filter Time	16 bit Unsigned		200	r/w		

Index	Sub-index	Name	Length	Value Range	Default	Access Rights	Data Storage?	Smart Sensor Profile
78		All-Time Run Time Event Time						
78	1	Event Time	32 bit Unsigned	0..2147483647	0	rw	y	
79		Resettable Run Time Event Time						
79	1	Event Time	32 bit Unsigned	0..2147483647	0	rw	y	
96		Mode Type	8 bit Unsigned	0 = Voltage, 1 = Current	0	r		
16512		MDC Descriptor		Measuring Data Channel Descriptor - Smart Sensor Profile 2nd Edition				y
16512	1	Lower Limit	32 bit Integer			r		y
16512	2	Upper Limit	32 bit Integer			r		y
16512	3	Unit	16 bit Unsigned	1209 = A, 1240 = V		r		y
16512	4	Scale	8 bit Unsigned	8 (uA), 3(mV)		r		y

IO-Link Events

Events are acyclic transmissions from the IO-Link device to the IO-Link master. Events can be error messages and/or warning or maintenance data.

Code	Type	Name	Description
25376 (0x6320)	Error	Parameter error	Check data sheet and values
35000 (0x8CA0)	Warning	All-time Run Time Event	Event indicating the corresponding configured running time has elapsed.
35001 (0x8CA1)	Warning	Resettable Run Time Event	Event indicating the corresponding configured running time has elapsed.